

X8 Power Source 600 MV



OVERSIGT

Provides 600 A with a 40% duty cycle. The multi-voltage power source is suitable for the most common electrical network voltages. Requires a 63 A plug. Control Pad and X8 Cooler always included with the power source.

TEKNISKE SPECIFIKATIONER

X8 Power Source 600 MV

Produktkode	X8100601100 (Incl. X8 Control Pad and X8 Cooler) Power upgrade 600 for X8 Power Source - X8560000
Netspænding 3~ 50/60 Hz	220 - 230 V ± 10 % 380 - 460 V ± 10 %
Sikring, 380 - 460 V	35 A
Tomgangseffekt (MMA) (uden køler og trådboks, blæsere OFF)	44 - 53 W
Tomgangseffekt (MMA) (uden køler og trådboks, blæsere ON)	99 - 111 W
Tomgangseffekt (MMA) (med køler, uden trådboks, blæsere ON)	121 - 137 W
Output 40 % ED	600 A
Output 60 % ED	530 A
Output 100 % ED	440 A
Svejsestrøms- og spændingsområde, MIG @ 220 V	10A/10V - 600A/47V
Svejsestrøms- og spændingsområde, MIG @ 380 V	10A/10V - 600A/57V
Svejsestrøms- og spændingsområde, MMA @ 220 V	10A/10V - 600A/47V
Svejsestrøms- og spændingsområde, MMA @ 380 V	10A/10V - 600A/58.5V
Anbefalet generatoreffekt (min)	40 kVA
Tomgangsspænding (MMA)	50 V
Udvendige mål L x B x H	921 x 348 x 795 mm
Vægt (uden tilbehør)	95 kg

X8 Power Source 600 MV

Driftstemperaturområde	-20...+40 °C
Sikring, 220 – 230 V	63 A