

# X8 Power Source 400 MV



## OVERSIGT

Provides 400 A with a 60% duty cycle. The multi-voltage power source is suitable for the most common electrical network voltages. Control Pad always included with the power source. X8 Cooler not included.

## TEKNISKE SPECIFIKATIONER

### X8 Power Source 400 MV

Produktkode	X8100400101 - X8 Power Source 400 MV, CUSTOM (Work Pack + WiseFusion)
Netspænding 3~ 50/60 Hz	220 - 230 V $\pm 10$ % 380 - 460 V $\pm 10$ %
Sikring	32 A
Sikring, 380 - 460 V	63 A
Tomgangseffekt (MMA) (uden køler og trådboks, blæsere OFF)	44 - 53 W
Tomgangseffekt (MMA) (uden køler og trådboks, blæsere ON)	99 - 111 W
Output 60 % ED	400 A
Output 100 % ED	320 A
Svejsestrøms- og spændingsområde, MIG @ 220 V	20 A/14 V - 400 A/50 V
Svejsestrøms- og spændingsområde, MIG @ 380 V	20 A/14 V - 400 A/50 V
Svejsestrøms- og spændingsområde, MMA @ 220 V	15 A/20 V - 400 A/58 V
Svejsestrøms- og spændingsområde, MMA @ 380 V	15 A/20 V - 400 A/58 V
Anbefalet generatoreffekt (min)	35 kVA
Tomgangsspænding (MMA)	50 V
Udvendige mål L x B x H	921 x 348 x 795 mm
Vægt (uden tilbehør)	95 kg
Driftstemperaturområde	-20...+40 °C